

## **ULTRASENSOR 2**

### CHARACTERISTICS

- ULTRA SMALL:
   SMALLEST SENSOR ON
   THE MARKET TODAY.
   SMALL SIZE MEANS
   EASIER INSTALLATION ON
   TRICKY MACHINERY.
- ULTRA FAST:

   NO MECHANICAL
   MOVING PARTS MEANS
   THE SENSOR CAN READ

   ANY PRACTICAL CYCLE
   SPEED.
- ULTRA RELIABLE:
   COMPLETELY SOLID STATE
   OPERATION FOR HIGH
   RELIABILITY AND
   DURABILITY.
- IP 67 PROTECTION.
- FULLY POTTED SOLID STATE DEVICE: MEANS CIRCUIT IS ISOLATED FROM THE ENVIRONMENT.
- 2 LED:
  - GREEN DIAGNOSTIC LED
  - ORANGE MONITORING LED DIAGNOSTIC
- NPN AND PNP SIGNAL:
   BOTH INCLUDED AS
   STANDARD.
- M12 HEAVY DUTY
   METAL CONNECTOR:
   PROVIDES ROBUST
   WIRING SOLUTIONS.

### APPLICATIONS

SMX, SMP, SMO, NP
 AND NPR+ PROGRESSIVE
 SYSTEMS

Patented: Ultrasensor technology is protected by international patents.

Patented: US 20080284415 A1

# ULTRASENSOR 2 ULTRA SMALL, ULTRA FAST, ULTRA RELIABLE

The **UltraSensor 2** has been designed as a next generation replacement of Proximity and micro switch systems for monitoring spool movement in progressive divider elements. A single model will work with all standard SMX, SMP, SMO, nP and nPR+ divider blocks as a screw-on accessory without requiring special arrangement or modification to the spool. The patented concept works by monitoring magnetic flux variations through a Hall-effect sensor as the spool enters the sensing range. There are no moving parts which means the solid state device is completely wear free.



**NEW IMPROVEMENTS** 

The device is equipped with **2 LED**:

- **1. MONITORING LED (ORANGE)**: allows you to see the output signal. LED signal indicate a good function of the spool.
- **2. DIAGNOSTIC LED (GREEN)**: At power-on the number of pulses indicates the magnetic flux level. Pulses number is from 0 to 10. 5 blinking are standard pulses which shown a good function of device. Thanks to this diagnostic system you can verify the correct reading of magnetic field.

NPN and PNP connection options are standard within the same sensor.

→ NEW	Power-on diagnostic LED	Version 2	
→ NEW	Metallic connector		
→ NEW	Short-circuit protection		
→ NEW	Advanced sensing algorithm		
→ NEW	Interference resistant circuitry more robust than a normal prox. switch!		
→ NEW	Protection against reverse polarity		






SENSOR FOR SMP - 1655306 - 1655348 (SS 316)





SENSOR FOR SMO, NP AND NPR+ - 1655308 - 1655342 (SS 316)








# **ULTRASENSOR 2**


TECHNICAL CHARACTERISTICS				
Material	Stainless steel AISI 316 - Nickel-plated brass			
Max. Cycle per minute	1000			
Voltage	8 ÷ 28 V DC			
Short circuit protection	SI			
Protection degree	IP 67			
Operating temperature	-25°C ÷ +60 °C (-13÷ +158 °F)			
Connector	M12x1			
Output signals	NPN 2A - PNP 0,7A			
Max allowable pressure on the front sensor surface	400 bar (5800 psi)			

#### **MOUNTING INFORMATION**

	CLAMPING TORQUE	
SMX	10 Nm +-5%	
SMO- nP - nP Aluminium - nPr+	8 Nm	

### **OPERATING PRINCIPLE**





Normally, the magnetic field is balanced around the hall sensor. With the spool in the sensing range, the flux density is modified allowing the Hall Effect sensor to detect the presence of the spool. The use of a magnetic flex variation allows an extended sensing zone which avoids problems on systems with low flow rates and backpressure where the spool can often stop or bounce on the sensing surface.

### **ORDERING INFORMATION**

DESCRIPTION	MATERIAL	PART. NO.
Sensor for SMP	Nickel-plated brass	1655306
Selisor for Sivir	Stainless steel AISI 316	1655348
Sensor for SMX	Nickel-plated brass	1655305
Sensor for Sivia	Stainless steel AISI 316	1655340
Sensor for SMO - nP - nPR+	Nickel-plated brass	1655308
Sensor for sivio in the first	Stainless steel AISI 316	1655342

ACCESSORIES			
DESCRIPTION	PART. NO.		
M12 female connector	0039999		
5 m cable, M12 female connector	0039815		
2 m cable, M12 female connector	0039168		
2 m cable, 90°- M12 female connector	0039830		

Distributor Info:

C2118PE WK 02/23

Dropsa products can be purchased from Dropsa subsidiary and Dropsa sales representatives, visit <a href="www.dropsa.com/contact">www.dropsa.com/contact</a> or contact us <a href="mailto:sales@dropsa.com/contact">sales@dropsa.com/contact</a> or contact us <a href="mailto:sales@dropsa.com/contact/">sales@dropsa.com/contact/</a> or contact/<a href="mailto:sales@dropsa.com/contact/">sales@dropsa.com/contact/<a href="mailto:sales@dropsa.com/contact/">sales@dropsa.com/contact/<a href="mailto:sales@dropsa.com/contact/">sales@dropsa.com/contact/<a href="mailto:sales@dropsa.com/contact/">sales@dro